



kiCad



kiCad

KiCad

19 de febrer de 2018

Índex

1	Introducció	1
1.1	KiCad	1
1.2	Fitxers i directoris de KiCad	1
2	Instal·lació i configuració	3
2.1	Opcions de visualització	3
2.2	Instal·lació de la configuració predeterminada	3
2.3	Modifying the default configuration	3
2.4	Paths configuration	3
2.5	Initialization of external utilities	4
2.5.1	Selection of text editor	5
2.5.2	Selection of PDF viewer	5
2.6	Creating a new project	5
2.7	Importing a foreign project	6
3	Using KiCad project manager	7
3.1	Project manager window	7
3.2	Panell per llançar les utilitats	7
3.3	Vista en arbre del projecte	8
3.4	Barra d'eines superior	8
4	Project templates	10
4.1	Ús de plantilles	10
4.2	Template Locations:	11
4.3	Creating templates	11
4.3.1	Required File:	12
4.3.2	Fitxers opcionals:	13

Manual de referència

Copyright

This document is Copyright © 2010-2018 by its contributors as listed below. You may distribute it and/or modify it under the terms of either the GNU General Public License (<http://www.gnu.org/licenses/gpl.html>), version 3 or later, or the Creative Commons Attribution License (<http://creativecommons.org/licenses/by/3.0/>), version 3.0 or later.

Totes les marques comercials citades en aquesta guia pertanyen als seus propietaris legítims.

Contribuïdors

Jean-Pierre Charras, Fabrizio Tappero.

Traducció

Robert Antoni Buj Gelonch <rbuj@fedoraproject.org>, 2016

Realimentació

Si us plau, adreceu aquí els vostres informes d'errors de programari, suggeriments o per a noves versions:

- Quant a la documentació de KiCad: <https://github.com/KiCad/kicad-doc/issues>
- Quant al programari de KiCad: <https://bugs.launchpad.net/kicad>
- About KiCad translation: <https://github.com/KiCad/kicad-i18n/issues>

Data de publicació i versió del programari

2015, May 21.

Capítol 1

Introducció

1.1 KiCad

KiCad és una eina de programari de codi obert per a la creació de diagrames d'esquemes electrònics i plaques de circuits impresos. Sota la seva aparença singular, KiCad incorpora un recull elegant de les següents eines de programari:

- **KiCad**: Project manager
- **Eeschema**: Schematic editor and component editor
- **Pcbnew**: Circuit board layout editor and footprint editor
- **GerbView**: Gerber viewer

3 utility tools are also included:

- **Bitmap2Component**: Component maker for logos. It creates a schematic component or a footprint from a bitmap picture.
- **PcbCalculator**: A calculator that is helpful to calculate components for regulators, track width versus current, transmission lines, etc.
- **PI Editor**: Page layout editor.

Aquestes eines generalment s'executen des del gestor del projecte, però també es poden executar com a eines independents.

KiCad no presenta cap limitació quan a la mida de la placa, pot gestionar fins a 32 capes de coure, 14 capes tècniques i 4 capes auxiliars.

KiCad can create all the files necessary for building printed circuit boards, including:

- Fitxers Gerber per als foto-plòters
- fitxers de perforació
- fitxers d'ubicació de components

En ser codi obert (amb llicència GPL), KiCad representa l'eina ideal per als projectes orientats a la creació de maquinari electrònic amb un gust de codi obert.

KiCad is available for Linux, Windows and Apple macOS.

1.2 Fitxers i directoris de KiCad

KiCad crea i utilitza els fitxers (i els directoris) amb les següents extensions específiques de fitxers per a l'edició d'esquemes i de plaques.

Ficher del gestor del projecte:

*.pro	Fitxer de mida reduïda que conté alguns paràmetres per al projecte actual, incloent-hi la llista de biblioteques de components.
-------	---

Fitxers de l'editor d'esquemes:

*.sch	Schematic files, which do not contain the components themselves.
*.lib	Schematic component library files, containing the component descriptions: graphic shape, pins, fields.
*.dcm	Schematic component library documentation, containing some component descriptions: comments, keywords, reference to data sheets.
*_cache.lib	Schematic component library cache file, containing a copy of the components used in the schematic project.
sym-lib-table	Symbol library list (<i>symbol library table</i>): list of symbol libraries available in the schematic editor.

Fitxers i directoris de l'editor de plaques:

*.kicad_pcb	Board file containing all info but the page layout.
*.pretty	Footprint library folders. The folder itself is the library.
*.kicad_mod	Footprint files, containing one footprint description each.
*.brd	Board file in the legacy format. Can be read, but not written, by the current board editor.
*.mod	Footprint library in the legacy format. Can be read by the footprint or the board editor, but not written.
fp-lib-table	Footprint library list (<i>footprint library table</i>): list of footprint libraries (various formats) which are loaded by the board or the footprint editor or CvPcb.

Fitxers comuns

*.kicad_wks	Page layout description files, for people who want a worksheet with a custom look.
*.net	Netlist file created by the schematic, and read by the board editor. This file is associated to the .cmp file, for users who prefer a separate file for the component/footprint association.

Fitxers especials

*.cmp	Association between components used in the schematic and their footprints. It can be created by Pcbnew and imported by Eeschema. Its purpose is to import changes from Pcbnew to Eeschema, for users who change footprints inside Pcbnew (for instance using <i>Exchange Footprints</i> command) and want to import these changes in schematic.
-------	---

Altres fitxers:

Es generen amb KiCad per a la fabricació o la documentació.

*.gbr	Gerber files, for fabrication.
*.drl	Drill files (Excellon format), for fabrication.
*.pos	Position files (ASCII format), for automatic insertion machines.
*.rpt	Report files (ASCII format), for documentation.
*.ps	Plot files (Postscript), for documentation.
*.pdf	Plot files (PDF format), for documentation.
*.svg	Plot files (SVG format), for documentation.
*.dxf	Plot files (DXF format), for documentation.
*.plt	Plot files (HPGL format), for documentation.

Capítol 2

Instal·lació i configuració

2.1 Opcions de visualització

Hardware accelerated renderer in Pcbnew and Gerbview requires video card with support of OpenGL v2.1 or higher.

2.2 Instal·lació de la configuració predeterminada

The default configuration file named **kicad.pro** is supplied in kicad/template. It serves as a template for any new project and is used to set the list of library files loaded by Eeschema. A few other parameters for Pcbnew (default text size, default line thickness, etc.) are also stored here.

Another default configuration file named **fp-lib-table** may exist. It will be used only once to create a footprint library list; otherwise the list will be created from scratch.

2.3 Modifying the default configuration

The default **kicad.pro** file can be freely modified, if desired.

Verifiez que tinguem accés d'escriptura a kicad/template/kicad.pro

Run KiCad and load **kicad.pro** project.

Run Eeschema via KiCad manager. Modify and update the Eeschema configuration, to set the list of libraries you want to use each time you create new projects.

Run Pcbnew via KiCad manager. Modify and update the Pcbnew configuration, especially the footprint library list. Pcbnew will create or update a library list file called **footprint library table**. There are 2 library list files (named fp-lib-table): The first (located in the user home directory) is global for all projects and the second (located in the project directory) is optional and specific to the project.

2.4 Paths configuration

In KiCad, one can define paths using an *environment variable*. A few environment variables are internally defined by KiCad, and can be used to define paths for libraries, 3D shapes, etc.

This is useful when absolute paths are not known or are subject to change (e.g. when you transfer a project to a different computer), and also when one base path is shared by many similar items. Consider the following which may be installed in varying locations:


- Eeschema component libraries
- Pcbnew footprint libraries
- 3D shape files used in footprint definitions

For instance, the path to the *connect.pretty* footprint library, when using the **KISYSMOD** environment variable, would be defined as *#{KISYSMOD}/connect.pretty*

This option allows you to define a path using an environment variable, and add your own environment variables to define personal paths, if needed.

KiCad environment variables:

KICAD_PTEMPLATES	Templates used during project creation. If you are using this variable, it must be defined.
KICAD_SYMBOL_DIR	Base path of symbol library files.
KIGITHUB	Frequently used in example footprint lib tables. If you are using this variable, it must be defined.
KISYS3DMOD	Base path of 3D shapes files, and must be defined because an absolute path is not usually used.
KISYSMOD	Base path of footprint library folders, and must be defined if an absolute path is not used in footprint library names.



Note also the environment variable **KIPRJMOD** is **always** internally defined by KiCad, and is the **current project absolute path**.


For instance, *#{KIPRJMOD}/connect.pretty* is always the *connect.pretty* folder (the pretty footprint library) found inside **the current project folder**.

If you modify the configuration of paths, please quit and restart KiCad to avoid any issues in path handling.

2.5 Initialization of external utilities

You may define your favorite text editor and PDF viewer. These settings are used whenever you want to open a text or PDF file.

These settings are accessible from the Preference menu:



2.5.1 Selection of text editor

Before using a text editor to browse/edit files in the current project, you must choose the text editor you want to use.

Select *Preferences* → *Set Text Editor* to set the text editor you want to use.

2.5.2 Selection of PDF viewer

You may use the default PDF viewer or choose your own.

To change from the default PDF viewer use *Preferences* → *PDF Viewer* → *Set PDF Viewer* to choose the PDF viewer program, then select *Preferences* → *PDF Viewer* → *Favourite PDF Viewer*.

On Linux the default PDF viewer is known to be fragile, so selecting your own PDF viewer is recommended.

2.6 Creating a new project

In order to manage a KiCad project consisting of schematic files, printed circuit board files, supplementary libraries, manufacturing files for photo-tracing, drilling and automatic component placement files, it is recommended to create a project as follows:

- **Creació d'un directori de treball per al projecte** (amb KiCad o de qualsevol altra manera).
- **En aquest directori, utilitzeu KiCad per a crear un fitxer de projecte** (el fitxer amb l'extensió .pro) a través de les icones «Crea un nou projecte» o «Crea un nou projecte des d'una plantilla».



Avís

Use a unique directory for each KiCad project. Do not combine multiple projects into a single directory.

KiCad creates a file with a .pro extension that maintains a number of parameters for project management (such as the list of libraries used in the schematic). Default names of both main schematic file and printed circuit board file are derived from the name of the project. Thus, if a project called **example.pro** was created in a directory called **example**, the default files will be created:

example.pro	Project management file.
example.sch	Main schematic file.
example.kicad_pcb	Printed circuit board file.
example.net	Netlist file.
example.*	Various files created by the other utility programs.
example-cache.lib	Library file automatically created and used by the schematic editor containing a backup of the components used in the schematic.

2.7 Importing a foreign project

KiCad is able to import files created using other software packages. Currently only Eagle 6.x or newer (XML format) is supported.

To import a foreign project, you need to select either a schematic or a board file in the import file browser dialog. Imported schematic and board files should have the same base file name (e.g. project.sch and project.brd). Once the requested files are selected, you will be asked to select a directory to store the imported files, which are going to be saved as a KiCad project.

Capítol 3

Using KiCad project manager


KiCad project manager (`kicad` or `kicad.exe`) is a tool which can easily run the other tools (schematic and PCB editors, Gerber viewer and utility tools) when creating a design.

L'execució de les altres eines des del gestor KiCad té alguns avantatges:

- Proves creuades entre l'editor d'esquemàtics i l'editor de plaques.
- Proves creuades entre l'editor d'esquemàtics i el selector d'empremtes (CvPcb).

However, you can only edit the current project files. When these tools are run in *stand alone* mode, you can open any file in any project but cross probing between tools can give strange results.

3.1 Project manager window



La finestra principal de KiCad es compon d'una vista en arbre del projecte, un panell de llançament que conté els botons que s'utilitzen per executar les diverses eines de programari, i una finestra de missatges. El menú i la barra d'eines es poden utilitzar per a crear, llegir i desar els fitxers del projecte.

3.2 Panell per llançar les utilitats


KiCad allows you to run all standalone software tools that come with it.

El panell de llançament està format pels 8 botons de sota que corresponen a les següents ordres (d'1 a 8, d'esquerra a dreta):



1	Eeschema	Schematic editor.
2	LibEdit	Component editor and component library manager.
3	Pcbnew	Board layout editor.
4	FootprintEditor	Footprint editor and footprint library manager.
5	Gerbview	Gerber file viewer. It can also display drill files.
6	Bitmap2component	Tool to build a footprint or a component from a B&W bitmap image to create logos.
7	Pcb Calculator	Tool to calculate track widths, and many other things.
8	Pl Editor	Page layout editor, to create/customize frame references.

3.3 Vista en arbre del projecte



Double-clicking on the schematic file runs the schematic editor, in this case opening the file **pic_programmer.sch**.





Double-clicking on the board file runs the layout editor, in this case opening the file **pic_programmer.kicad_pcb**.

En fer clic dret en qualsevol dels fitxers a l'arbre del projecte permet la manipulació genèrica del fitxer.

3.4 Barra d'eines superior



KiCad top toolbar allows for some basic file operations:

	Create a new project. If the default template file (kicad.pro) is found in kicad/template , it is copied into the working directory.
	Create a new project from an existing template.
	Open an existing project.
	Update and save the current project tree.



Create a zip archive of the whole project. This includes schematic files, libraries, PCB, etc.



Refresh the tree view, sometimes needed after a tree change.

Capítol 4

Project templates

Using a project template facilitates setting up a new project with predefined settings. Templates may contain pre-defined board outlines, connector positions, schematic elements, design rules, etc. Complete schematics and/or PCBs used as seed files for the new project may even be included.


4.1 Ús de plantilles

The *File* → *New Project* → *New Project from Template* menu will open the Project Template Selector dialog:



A single click on a template's icon will display the template information, and a further click on the OK button creates the new project. The template files will be copied to the new project location and renamed to reflect the new project's name.

Després de seleccionar una plantilla:



4.2 Template Locations:

KiCad looks for template files in the following paths:

- System templates: <kicad bin dir>/../share/kicad/template/
- User templates:
 - Unix: ~/kicad/templates/
 - Windows: C:\Documents and Settings\username\My Documents\kicad\templates
 - Mac: ~/Documents/kicad/templates/
- When the environment variable KICAD_PTEMPLATES is defined there is a third tab, Portable Templates, which lists templates found at the KICAD_PTEMPLATES path.

4.3 Creating templates


The template name is the directory name where the template files are stored. The metadata directory is a subdirectory named **meta** containing files describing the template.

All files and directories in a template are copied to the new project path when a project is created using a template, except **meta**.


When a new project is created from a template, all files and directories starting with the template name will be renamed with the new project file name, excluding the file extension.

The metadata consists of one required file, and may contain optional files. All files must be created by the user using a text editor or previous KiCad project files, and placed into the required directory structure.

Here is an example showing project files for **raspberrypi-gpio** template:



And the metadata files:



4.3.1 Required File:

meta/info.html	HTML-formatted information describing the template.
----------------	---

The <title> tag determines the actual name of the template that is exposed to the user for template selection. Note that the project template name will be cut off if it's too long. Due to font kerning, typically 7 or 8 characters can be displayed.

Using HTML means that images can be easily in-lined without having to invent a new scheme. Only basic HTML tags can be used in this document.

Here is a sample **info.html** file:

```
<!DOCTYPE HTML PUBLIC "-//W3C//DTD HTML 4.0 Transitional//EN">
<HTML>
<HEAD>
<META HTTP-EQUIV="CONTENT-TYPE" CONTENT="text/html;
charset=windows-1252">
<TITLE>Raspberry Pi - Expansion Board</TITLE>
<META NAME="GENERATOR" CONTENT="LibreOffice 3.6 (Windows)">
<META NAME="CREATED" CONTENT="0;0">
<META NAME="CHANGED" CONTENT="20121015;19015295">
</HEAD>
<BODY LANG="fr-FR" DIR="LTR">
```



```
<P>This project template is the basis of an expansion board for the
<A HREF="http://www.raspberrypi.org/" TARGET="blank">Raspberry Pi $25
ARM board.</A> <BR><BR>This base project includes a PCB edge defined
as the same size as the Raspberry-Pi PCB with the connectors placed
correctly to align the two boards. All IO present on the Raspberry-Pi
board is connected to the project through the 0.1&quot; expansion
headers. <BR><BR>The board outline looks like the following:
</P>
<P><IMG SRC="brd.png" NAME="brd" ALIGN=BOTTOM WIDTH=680 HEIGHT=378
BORDER=0><BR><BR><BR><BR>
</P>
<P>(c) 2012 Brian Sidebotham<BR>(c) 2012 KiCad Developers</P>
</BODY>
</HTML>
```

4.3.2 Folders optional:

meta/icon.png	A 64 x 64 pixel PNG icon file which is used as a clickable icon in the template selection dialog.
---------------	---

Any other image files used by **meta/info.html**, such as the image of the board file in the dialog above, are placed in this folder as well.